FLUKE®

51 & 52 Series II

Thermometer

Users Manual

English
September 1999
© 1999 Fluke Corporation, All rights reserved. Printed in USA
All product names are trademarks of their respective companies.

Limited Warranty & Limitation of Liability

This Fluke product will be free from defects in material and workmanship for 3 years from the date of purchase. This warranty does not cover fuses, disposable batteries or damage from accident, neglect, misuse or abnormal conditions of operation or handling. Resellers are not authorized to extend any other warranty on Fluke's behalf. To obtain service during the warranty period, send your defective tester to the nearest Fluke Authorized Service Center with a description of the problem.

THIS WARRANTY IS YOUR ONLY REMEDY. NO OTHER WARRANTIES, SUCH AS FITNESS FOR A PARTICULAR PURPOSE, ARE EXPRESSED OR IMPLIED. FLUKE IS NOT LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL OR CONSEQUENTIAL DAMAGES OR LOSSES, ARISING FROM ANY CAUSE OR THEORY. Since some states or countries do not allow the exclusion or limitation of an implied warranty or of incidental or consequential damages, this limitation of liability may not apply to you.

Fluke Corporation	Fluke Europe B.V.
P.O. Box 9090	P.O. Box 1186
Everett WA	5602 B.D. Eindhoven
98206-9090	The Netherlands

10/96

Table of Contents

Title	Page
Introduction	1
Contacting Fluke	1
Getting Started	4
Components	5
Display Elements	6
Buttons	7
Using the Thermometer	9
Changing Setup Options	9
Entering or Exiting Setup	9
Setup Options	9
Changing a Setup Option	10
Measuring Temperatures	11
Connecting a Thermocouple	11
Displaying Temperatures	11
Holding the Displayed Readings	12
Viewing the MIN, MAX, and AVG Readings	12
Using the Offset to Adjust for Probe Errors	12

Maintenance 13
Replacing the Batteries 13
Cleaning the Case and Holster 13
Calibration 13
Specifications 13
Environmental 13
General 14
80 PK-1 Thermocouple (supplied with thermometer) 14
Electrical 14
Replacement Parts and Accessories 15

51 & 52 Series II

Introduction

The Fluke Model 51 and Model 52 Thermometers (“the thermometer”) are microprocessor-based, digital thermometers designed to use external J-, K-, T-, and E-type thermocouples (temperature probes) as temperature sensors.

Use the thermometer only as specified in this manual. Otherwise, the protection provided by the meter may be impaired.

Refer to safety information in Table 1 and meter symbols in Table 2.

Contacting Fluke

To order accessories, receive assistance, or locate the nearest Fluke distributor or Service Center, call:

1-888-993-5853 in USA & Canada
+31-402-678-200 in Europe
+81-3-3434-0181 in Japan
+65-738-5655 in Singapore
+1-425-446-5500 from other countries

Address correspondence to:

Fluke Corporation
P.O. Box 9090
Everett, WA 98206-9090
USA

Fluke Europe B.V.
P.O. Box 1186
5602 BD Eindhoven
The Netherlands

Visit us on the World Wide Web at: www.fluke.com

Table 1. Safety Information

⚠Warning

A Warning identifies conditions and actions that pose hazards to the user. To avoid electrical shock or personal injury, follow these guidelines:

- **Before using the thermometer inspect the case. Do not use the thermometer if it appears damaged. Look for cracks or missing plastic. Pay particular attention to the insulation around the connectors.**
- **Disconnect the thermocouple(s) from the thermometer before opening the case.**
- **Replace the batteries as soon as the battery indicator (🔋) appears. The possibility of false readings can lead to personal injury.**
- **Do not use the thermometer if it operates abnormally. Protection may be impaired. When in doubt, have the thermometer serviced.**
- **Do not operate the thermometer around explosive gas, vapor, or dust.**
- **Do not apply more than the rated voltage, as marked on the thermometer, between the thermocouple(s), or between any thermocouple and earth ground.**

Table 1. Safety Information (cont.)

⚠Warning (cont.)

- ***Model 52:*** **Measurement errors may occur if voltages on the measurement surfaces result in potentials greater than 1 V between the two thermocouples. When potential differences are anticipated between the thermocouples, use electrically insulated thermocouples.**
- **When servicing the thermometer, use only specified replacement parts.**
- **Do not use the thermometer with any part of the case or cover removed.**

Caution

A Caution identifies conditions and actions that may damage the meter or the equipment under test.

- **Use the proper thermocouples, function, and range for your thermometer.**
- **Do not attempt to recharge the batteries.**
- **To prevent explosion, do not throw batteries into a fire.**
- **Follow local laws or regulations when disposing of batteries.**
- **Match the + and – polarities of the battery with the battery case.**

Table 2. International Symbols

⚠	Refer to the manual for information about this feature.	CE	Complies with European Union directives.
	Battery.	C SP US	Complies with relevant Canadian Standards Association directives.

Getting Started

Everything in this *Users Manual* applies both to Models 51 and 52 unless otherwise indicated.

To become familiar with the thermometer, study the following:

- Figure 1 and Table 3 describe the components.
- Figure 2 and Table 4 describe the display.
- Table 5 describes the functions of the buttons.

Then read the following sections.

Components



aas01f.eps

Figure 1. Components

Table 3. Components

①	Thermocouple T1 input
②	*Model 52:* Thermocouple T2 input
③	Holster
④	Display
⑤	Buttons
⑥	Battery door
⑦	Batteries

Display Elements



aas02f.eps

Figure 2. Display Elements

Table 4. Display Elements

①	The thermocouple measurement includes an offset. See "Changing Setup Options."
②	The displayed readings do not change.
③	A shift function is in progress.
④	Setup is in progress.
⑤	Low battery. Replace the batteries.
⑥	Primary Display. *Model 51*: T1 reading. *Model 52:* T1, T2, or T1-T2 reading.
⑦	The temperature unit.
⑧	Secondary Display: MAX, MIN, AVG, or offset. *Model 52:* T1or T2 reading.
⑨	The thermocouple type.
⑩	Time Display: The elapsed time.

Buttons

Table 5. Buttons

⏻	Press ⏻ to turn the thermometer on or off.
(Shift function)	Press (Shift function), MIN MAX (CANCEL) to stop displaying the minimum, maximum, and average readings in the secondary display.
☼	Press ☼ to turn the backlight on and off. The backlight turns off after 2 minutes without any button presses. If the battery is low, the backlight is disabled.
MIN MAX	Press MIN MAX to step through the maximum, minimum, and average readings. When viewing logged readings, shows the maximum, minimum, and average of the logged readings. Press (Shift function), MIN MAX (CANCEL) to turn off this display.
°C °F K	Press °C °F K to switch between Celsius (°C), Fahrenheit (°F), and Kelvin (K).
HOLD	Press HOLD to freeze or unfreeze the displayed readings. Press HOLD when turning on the thermometer to test the display. All display elements appear.
T1 T2 T1-T2	*Model 52:* Press T1 T2 T1-T2 to toggle showing the T1, T2, and T1-T2 (differential temperature measurement) in the primary or secondary display.

Table 5. Buttons (cont.)

SETUP	Press SETUP to start or exit Setup. (See "Changing Setup Options.")
△	Press △ to scroll to the Setup option you want to change. Press △ to increase the displayed setting.
▽	Press ▽ to scroll to the Setup option you want to change. Press ▽ to decrease the displayed setting.
ENTER	Press ENTER to enter a Setup option. Press ENTER again to store the displayed setting in memory.

Using the Thermometer

1. Plug the thermocouple(s) into the input connector(s).
2. Press ⏻ to turn on the thermometer.

After 1 second the thermometer displays the first reading. If no thermocouple is plugged into the selected input or the thermocouple is "open," the display shows "**- - - -**"

Changing Setup Options

Use Setup to change the thermocouple type, offset, sleep mode, and line frequency settings.

The thermometer stores the settings in its memory. Setup settings reset only when the batteries are removed for more than 2 minutes.

Entering or Exiting Setup

When the thermometer is in Setup mode, the display shows **SETUP**.

- Press SETUP to start or exit Setup.

Setup Options

Option	Menu Item	Settings
Thermocouple Type	**TYPE**	**J, K, T,** or **E**
Offset	**OFFSET**	**T1** or **T2** (Model 52)
Sleep Mode	SLP	on (sleep mode on) or OFF (sleep mode off)
Line Frequency	LInE	**50 H** (50 Hz) or **60 H** (60 Hz)

Changing a Setup Option

1. Press △ or ▽ to scroll to the setup option you want to change.
2. Press ENTER to indicate that you want to change this setting.
3. Press △ or ▽ until the setting you want to use appears on the display.
4. Press ENTER to store the new setting in memory.

Notes

Setup is disabled in MIN MAX mode.

Offset:

The primary display shows the temperature plus the offset and the secondary display shows the offset. Remember to reset the offset to 0.0 when it is no longer needed. The offset automatically resets to 0.0 when you change the thermocouple type. Model 52: You can store individual offsets for T1 and T2.

Sleep mode:

The thermometer enters sleep mode if no button press occurs for 20 minutes. Pressing any button wakes the thermometer and returns it to its previous state. Sleep mode becomes enabled each time you turn on the thermometer and is automatically disabled in MIN MAX mode.

Line frequency:

For optimum rejection of line noise, the thermometer must be set for the local line frequency.

Measuring Temperatures

Connecting a Thermocouple

To change the thermocouple type, see “Changing Setup Options.” The North American ANSI Color Code is:

Type	J	K	E	T	N
Color	Black	Yellow	Purple	Blue	Orange

1. Plug a thermocouple into the input connector(s). (Make sure that the polarity is correct.)
2. Set the thermometer for the correct thermocouple type.

Displaying Temperatures

1. Press [°C°F K] to select the correct temperature scale.
2. Hold or attach the thermocouple(s) to the measurement location.

   The temperature reading appears in the primary display.
3. *Model 52:* Press [T1 T2 T1-T2] to toggle between showing the T1, T2, and T1-T2 readings in the primary or secondary display.

Notes

The display shows "- - - -" when a thermocouple is not connected.

The display shows OL (overload) when the temperature being measured is outside the thermocouple's valid range.

Model 52: If only thermocouple T2 is connected, the T2 reading appears in the primary display.

Holding the Displayed Readings

1. Press HOLD to freeze the readings on the display.

   The display shows **HOLD**.

2. *Model 52:* Press T1 T2 T1-T2 to toggle showing the T1, T2, or T1-T2 readings in the primary or secondary display.

3. Press HOLD again to turn off the HOLD function.

Viewing the MIN, MAX, and AVG Readings

1. Press MIN MAX to step through the maximum (MAX), minimum (MIN), or the average (AVG) readings.

   The elapsed time since entering MIN MAX mode, or the time at which the minimum or maximum occurred, appears on the display.

2. Press ⬭, MIN MAX (CANCEL) to exit MIN MAX mode.

Using the Offset to Adjust for Probe Errors

Use the offset option in Setup to adjust the thermometer's readings to compensate for the errors of a specific thermocouple.

The allowable adjustment range is ± 5.0 °C or K, and ± 9.0 °F.

1. Plug the thermocouple into the input connector.

2. Place the thermocouple in a known, stable temperature environment (such as an ice bath or a dry well calibrator).

3. Allow the readings to stabilize.

4. In Setup change the offset until the primary display reading matches the calibration temperature. (See "Changing Setup Options.")

Maintenance

Replacing the Batteries

Refer to the safety information in Table 1 before replacing the batteries.

1. Turn off the thermometer if necessary.
2. Loosen the screw and remove the battery door.
3. Replace the three AA batteries.
4. Replace the battery door and tighten the screw.

Cleaning the Case and Holster

Use soap and water or a mild commercial cleaner.

Wipe with a damp sponge or soft rag.

Calibration

To ensure that the thermometer performs to its accuracy specifications, Fluke recommends that you calibrate the thermometer annually, starting one year after purchase.

To calibrate the thermometer, contact Fluke for the Service Center nearest you or follow the calibration procedure in the service manual listed in "Replacement Parts and Accessories."

Specifications

Environmental

Operating Temperature	–10 °C to 50 °C (14 °F to 122 °F)
Storage Temperature	–40 °C to +60 °C (–40 °F to +140 °F)
Humidity	0 % to 90 %: –10 °C to 35 °C (14 °F to 95 °F) 0 % to 70 %: –10 °C to 50 °C (14 °F to 122 °F)

General

Weight	280 g (10 oz)
Dimensions (without holster)	2.8 cm × 7.8 cm × 16.2 cm (1.1 in × 3 in × 6.4 in)
Battery	3 AA batteries
Certification	CE, cSAus (TÜV pending)
Safety	CSA C22.2 No. 1010.1 1992 EN 61010 Amendments 1, 2
CAT I	OVERVOLTAGE (Installation) CATEGORY I, Pollution Degree 2 per IEC1010-1*

* Refers to the level of Impulse Withstand Voltage protection provided. Equipment of OVERVOLTAGE CATEGORY I is equipment for connection to circuits in which measures are taken to limit the transient over voltages to an appropriate low level. Example include protect electronic circuits.

80 PK-1 Thermocouple (supplied with thermometer)

Type	Type K, Chromel Alumel, bead style
Temperature Range	–40 oC to +260 oC (–40 oF to +500 oF)
Accuracy	± 1.1 oC (± 2.0 oF)

Electrical

Measurement Range	J-type: –210 oC to +1200 oC (–346 oF to + 2192 oF) K-type: –200 oC to +1372 oC (–328 oF to +2501 oF) T-type: –250 oC to +400 oC (–418 oF to +752 oF) E-type: –150 oC to +1000 oC (–238 oF to +1832 oF)
Display Resolution	0.1 oC / oF / K < 1000o 1.0 oC / oF / K ≥ 1000o

Electrical (cont.)

Measurement Accuracy, T1, T2, or T1-T2 ***(Model 52)***	J-, K-, T-, and E-type: ±[0.05 % of reading + 0.3 °C (0.5 °F)] [below –100 °C (–148 °F): add 0.15 % of reading for J-, K-, E-, and N-type; and 0.45 % of reading for T-type]
Temperature Coefficient	0.01 % of reading + 0.03 °C per °C (0.05 °F per °F) outside the specified +18 °C to 28 °C (+64 °F to +82 °F) range [below –100 °C (–148 °F): add 0.04 % of reading for J-, K-, E-, and N-type; and 0.08 % of reading for T-type]
Maximum Differential Common Mode Voltage	1 V (Maximum voltage difference between T1 and T2)
Temperature Scale	ITS-90
Applicable Standards	NIST-175
Accuracy is specified for ambient temperatures between 18 °C (64 °F) and 28 °C (82 °F) for a period of 1 year. The above specifications do not include thermocouple error.	

Replacement Parts and Accessories

Accessory	Part Number
Holster and Flex Stand™ Assembly	1272438
AA NEDA 15A IEC LR6 batteries	376756
80PK-1 K-Type Bead Thermocouple	773135
CD-ROM	1276106
Service Manual	1276123